

# IceCap 250-MH Ballast

Model		250-MH
Description		120V
Lamp		MH-250W
Lamp Spec	Voltage	130V
	Current	2.1 Amps
Input Voltage		120V
Input Current		2.2A @ 120V
Input Power		262W
Power Factor		> 0.99
Total Harmonic Distortion		< 5%
Lamp Current Crest Factor		< 1.8
Operating Frequency		70-90KHz
Ignition Voltage		1.6KVp
Starting Time		< 5 seconds
Restarting Time (Warm Lamp)		5-6 Minutes
Minimum Starting Temp.		-25C
Max. Mounting Distance		33 Feet
Open Circuit Protection		Yes
Ignition Failure Protection		Yes
End of Lamp Life Protection		Yes
Flicker		None
Sound Rating		A
Enclosure Overall Dimension - metric		215 X 106 X 78 mm
Weight		6.4 lbs / 2.9 Kg
Average Ballast Life @ 50C		> 100,000 Hours?